



CYB EC16 & DEX16

Elevator Control Panel & Elevator Floor Expansion Board



EC16



DEX16

EC16 is the second generation of CYB's company elevator control panel. It can support fingerprint and RFID card verification through RS485 direct connection. Each EC16 can control maximum 16 floors and can be connected up to 7 DEX16 expansion boards. Each DEX16 assists EC16 to manage up to 16 floors, therefore, the EC16 and DEX 16 can control 128 floors in total, covering most of the market demand. The multi-time schedule can set a restriction on elevator entering designated floor at different time for different users. Yet, the lift direct access function can ensure only those who are authorized to gain access right passage to the assigned floor at a designated time. Once the identity authentication of elevator passengers is successful, the elevator will dispatch the elevator passengers to their destination.

Features (GL Exclusive Feature)



Maximum 128 Floors of Elevator Control (EC16 + DEX 16)



Multi-credential Authentications (Fingerprint, RFID, Dynamic QR Code, and Facial Recognition)[KF1100/1200]



Multiple Communication Modes: TCP/IP, USB



EC16 & DEX16 are equipped with 16 dual relay outputs



Direct Access to Designated Floor After Positive Verification



Supports Multi-time Schedule




Advanced Data Security Standard (Communication encrypted with AES256 and TLS1.2)


Specifications (GL Exclusive Feature)

<p>Model: EC16</p> <p>Capacity:</p> <p>Fingerprint: 30,000 Card: 100,000 Transactions: 200,000</p> <p>Communication</p> <p>TCP/IP, USB Host, Wiegand, RS485*</p> <p>Floor Button Control Relay</p> <p>16 Dual Relay</p> <p>Number of Ports</p> <p>2 TCP/IP, 2 Wiegand (26/34/66 bits), 1 RS485 (OSDP), 1 RS485 (expansion board)</p> <p>1 Open, 1 close, 1 AUX output, 1 AUX in, 1 voice output(coming soon), 1 LED Output(COMMRUN/PWR/GND), 1 FIRE,1 Emergency, 1 Power in, 1 USB 2.0 port</p>	<p>Additional Info Dimension(L*W): 165*230mm</p> <p>Operating Temperature: -20°C to 55°C</p> <p>Storage Temperature: -25°C to 65°C Operating Humidity: 10% to 90% RH</p> <p>Data Protection: AES256, HTTPS, Special Functions</p> <p>Protocol: ZKTeco A & C Push</p> <p>Supported QR Code Reader : QR500/600 SerCieosm</p> <p>RS485 address Set by DIP switch</p> <p>Max Supported Expansion Board: 7pcs (DEX16) over RS485</p> <p>Certifications</p> <p>CE, FCC, ISO9001, ISO14001</p> <p>ZKBio CVSecurity</p> <p>Power Supply</p> <p>DC 12V 3A</p>	<p>Model: DEX16</p> <p>Floor Button Control Relay</p> <p>16 Dual Relay</p> <p>Number of Ports</p> <p>1 RS485 IN 1 RS485 OUT</p> <p>RS485(OSDP)</p> <p>Additional Info</p> <p>Communication to EC16 : RS485</p> <p>Operating Temperature : -20°C to 55°C</p> <p>Storage Temperature: -25°C to 65°C</p> <p>Operating Humidity:10% to 90% RH</p> <p>Dimension(L*W):165*132mm</p> <p>Certifications</p> <p>CE, FCC, ISO9001, ISO14001</p> <p>Power Supply</p> <p>DC 12V 1A</p>
---	--	--


Configuration



Dimensions (mm)



EC16



DEX16